


# Fiberdyne Configuration 20



## 10Gb MPO Assemblies

Fiberdyne Part Number	Fiberdyne Configuration 20	Cable Type 50/125 OM3 (Max 300m)	Fiber Count	End A Connector	End B Connector	Guide Pin P=Pinned(Male) NP=Non-Pinned(Female)	Insertion Loss (IL) Standard / Low Loss*
FMT-020010-XXXM	10GBASE-SR	3mm Round Plenum OM3	12	MPO 1x12	MPO 1x12	NP-NP	<.75
FMT-020020-XXXM	10GBASE-SR	3mm Round Plenum OM3	12	MPO 1x12	MPO 1x12	NP-P	<.75
FMT-020030-XXXM	10GBASE-SR	3mm Round Plenum OM3	12	MPO 1x12	MPO 1x12	P-NP	<.75
FMT-020040-XXXM	10GBASE-SR	3mm Round Plenum OM3	12	MPO 1x12	MPO 1x12	P-P	<.75
FMT-020050-XXXM	10GBASE-SR	3mm Round Plenum OM3	12	MPO 1x12	MPO 1x12	NP-NP	<.35
FMT-020060-XXXM	10GBASE-SR	3mm Round Plenum OM3	12	MPO 1x12	MPO 1x12	NP-P	<.35
FMT-020070-XXXM	10GBASE-SR	3mm Round Plenum OM3	12	MPO 1x12	MPO 1x12	P-NP	<.35
FMT-020080-XXXM	10GBASE-SR	3mm Round Plenum OM3	12	MPO 1x12	MPO 1x12	P-P	<.35
Fiberdyne Part Number	Fiberdyne Configuration 20	Cable Type 50/125 OM4 (Max 550m)	Fiber Count	End A Connector	End B Connector	Guide Pin P=Pinned(Male) NP=Non-Pinned(Female)	Insertion Loss (IL) Standard / Low Loss*
FMT-020110-XXXM	10GBASE-SR	3mm Round Plenum OM4	12	MPO 1x12	MPO 1x12	NP-NP	<.75
FMT-020120-XXXM	10GBASE-SR	3mm Round Plenum OM4	12	MPO 1x12	MPO 1x12	NP-P	<.75
FMT-020130-XXXM	10GBASE-SR	3mm Round Plenum OM4	12	MPO 1x12	MPO 1x12	P-NP	<.75
FMT-020140-XXXM	10GBASE-SR	3mm Round Plenum OM4	12	MPO 1x12	MPO 1x12	P-P	<.75
FMT-020150-XXXM	10GBASE-SR	3mm Round Plenum OM4	12	MPO 1x12	MPO 1x12	NP-NP	<.35
FMT-020160-XXXM	10GBASE-SR	3mm Round Plenum OM4	12	MPO 1x12	MPO 1x12	NP-P	<.35
FMT-020170-XXXM	10GBASE-SR	3mm Round Plenum OM4	12	MPO 1x12	MPO 1x12	P-NP	<.35
FMT-020180-XXXM	10GBASE-SR	3mm Round Plenum OM4	12	MPO 1x12	MPO 1x12	P-P	<.35

\*Insertion Loss for Connector Only

## Fiberdyne Configuration 20

MPO-MPO, 12 Pin 8 Fiber to 12 Pin 8 Fiber, 10G, Type A, Key Up/Key Down					
Fiber Color Connector A	Lane Assignment Connector A	Position # Connector A	Position # Connector B	Lane Assignment Connector B	Fiber Color Connector B
Unused	TX1	1	1	RX1	Unused
Unused	RX1	2	2	TX1	Unused
Green	TX2	3	3	RX2	Green
Brown	RX2	4	4	TX2	Brown
Grey	TX3	5	5	RX3	Grey
White	RX3	6	6	TX3	White
Red	TX4	7	7	RX4	Red
Black	RX4	8	8	TX4	Black
Yellow	TX5	9	9	RX5	Yellow
Purple	RX5	10	10	TX5	Purple
Unused	TX6	11	11	RX6	Unused
Unused	RX6	12	12	TX6	Unused

# RoHS

FIBERDYNE LABS INC.

TITLE: Fiberdyne Configuration 20  
MPO-MPO, 8 Position, 10G  
Type A

SIZE <b>B</b>	DWG. NO. 075-11745-001	REV A
------------------	---------------------------	----------

SCALE: 1:1 ECR: 14006-001 SHEET 1 OF 1

Fiberdyne Labs Inc. Frankfort, NY  
www.fiberdyne.com

PROPRIETARY AND CONFIDENTIAL  
THE INFORMATION CONTAINED IN THIS DRAWING IS THE SOLE PROPERTY OF Fiberdyne Labs Inc. ANY REPRODUCTION IN PART OR AS A WHOLE WITHOUT THE WRITTEN PERMISSION OF Fiberdyne Labs Inc IS PROHIBITED.