


Fiberdyne Configuration 80



Single Mode MPO Assemblies

Fiberdyne Part Number	Fiberdyne Configuration 80	Cable Type OS2	Fiber Count	End A,B,C & D Connectors	Guide Pin P=Pinned(Male) NP=Non-Pinned(Female)	Insertion Loss (IL) Standard / Low Loss*
FMT-080010-XXXM	SM Laser	OS2 Round	48	MPO 1x12	NP-NP	<.75
FMT-080020-XXXM	SM Laser	OS2 Round	48	MPO 1x12	NP-P	<.75
FMT-080030-XXXM	SM Laser	OS2 Round	48	MPO 1x12	P-NP	<.75
FMT-080040-XXXM	SM Laser	OS2 Round	48	MPO 1x12	P-P	<.75
FMT-080050-XXXM	SM Laser	OS2 Round	48	MPO 1x12	NP-NP	<.35
FMT-080060-XXXM	SM Laser	OS2 Round	48	MPO 1x12	NP-P	<.35
FMT-080070-XXXM	SM Laser	OS2 Round	48	MPO 1x12	P-NP	<.35
FMT-080080-XXXM	SM Laser	OS2 Round	48	MPO 1x12	P-P	<.35

*Insertion Loss for Connector Only

Fiberdyne Configuration 80

MPO-MPO, SM,Trunk, Four 12 Pin 12 Fiber MPO to Four 12 Pin 12 Fiber MPO, Type A					
Fiber Color	Lane Assignment Connector A1	Position # Connector A1 Left Side	Position # Connector B2 Right Side	Lane Assignment Connector B2	Fiber Color
Blue	TX1	1	1	RX1	Blue
Orange	RX1	2	2	TX1	Orange
Green	TX2	3	3	RX2	Green
Brown	RX2	4	4	TX2	Brown
Grey	TX3	5	5	RX3	Grey
White	RX3	6	6	TX3	White
Red	TX4	7	7	RX4	Red
Black	RX4	8	8	TX4	Black
Yellow	TX5	9	9	RX5	Yellow
Purple	RX5	10	10	TX5	Purple
Pink	TX6	11	11	RX6	Pink
Aqua	RX6	12	12	TX6	Aqua
Fiber Color	Lane Assignment Connector B1	Position # Connector B1 Left Side	Position # Connector A2 Right Side	Lane Assignment Connector A2	Fiber Color
Blue	TX1	1	1	RX1	Blue
Orange	RX1	2	2	TX1	Orange
Green	TX2	3	3	RX2	Green
Brown	RX2	4	4	TX2	Brown
Grey	TX3	5	5	RX3	Grey
White	RX3	6	6	TX3	White
Red	TX4	7	7	RX4	Red
Black	RX4	8	8	TX4	Black
Yellow	TX5	9	9	RX5	Yellow
Purple	RX5	10	10	TX5	Purple
Pink	TX6	11	11	RX6	Pink
Aqua	RX6	12	12	TX6	Aqua

*Pin configuration show also applies for MPO C1 to MPO D2 & MPO D1 to MPO C2

RoHS

Fiberdyne Labs Inc. Frankfort, NY
www.fiberdyne.com

PROPRIETARY AND CONFIDENTIAL
THE INFORMATION CONTAINED IN THIS DRAWING IS THE SOLE PROPERTY OF Fiberdyne Labs Inc. ANY REPRODUCTION IN PART OR AS A WHOLE WITHOUT THE WRITTEN PERMISSION OF Fiberdyne Labs Inc IS PROHIBITED.

FIBERDYNE LABS INC.		
TITLE: Fiberdyne Configuration 80		
MPO-MPO, Four 12 Pin 12 Fiber to Four 12 Pin 12 Fiber, SM Type A		
SIZE B	DWG. NO. 075-11805-001	REV A
SCALE: 1:1	ECR: 14006-001	SHEET 1 OF 1